



818v3 Reference Audio Core

Network Audio Player/Preamplifier



Overview

Since its introduction in 1998, Meridian's 800 Reference Series has provided a platform from which the company has been able to showcase the very best in surround sound, DVD, CD, and network music playback. Through regular updates and iterations, it has also proven to be an outstanding benchmark against which performance standards have been set throughout the audio industry. 818, now in its third iteration, benefits from almost 20 years of 800 Series product innovation.

Meridian's Audio Core concept combines the source connectivity features of a high-performance preamplifier with a full suite of proprietary resolution enhancement technologies, and provides connectivity to Meridian's unique range of DSP Loudspeakers. In addition to its external source connectivity, with digital inputs supporting decoding of MQA sources for studio quality replay, 818 also provides an internal digital media source through a network connection to any Meridian Sooloos Digital Media System.

Maximum quality & I/O flexibility

818 is the highest performance two-channel preamplifier and Digital Media System end-point manufactured by Meridian.

Connecting at the centre of an incredible Meridian music system, 818 offers simple networked integration with any Meridian Sooloos Digital Media System plus an array of other sources including MQA. 818 features twin SpeakerLink outputs for "home run" connection in an all-digital

system with any of Meridian's SpeakerLink equipped DSP Loudspeakers. And as part of the 800 Reference Series, 818 features superb, high-quality analogue pre-amplifier outputs via both balanced and single-ended connectors, ensuring 818 can also be used in more traditional audio systems, where sophisticated DSP algorithms feeding the analogue outputs result in an even sweeter sound than before.

Meridian's SpeakerLink connection system delivers the highest quality digital signals to Meridian's DSP Loudspeakers on discreet, low-cost cables with simple connectors. SpeakerLink helps make a Meridian system easier to install and far less intrusive than other high-end audio systems. The advantage of the twin SpeakerLink output is that left and right loudspeakers can both be connected directly to the 818, further simplifying wiring structure and making cables even easier to hide.

818 may be used to control and configure Meridian DSP loudspeakers that do not have their own display, such as DSP in-wall systems. Features such as Bass, Treble, Balance, Enhanced Bass Alignment and Enhanced Boundary Control can be set from the Audio Control unit.

Resolution Enhancement

In common with the rest of Meridian's 800 Reference Series, 818 employs triple FIFO buffering, DSP upsampling and apodising filters to get the very best performance from all digital sources.

818 fully supports MQA – Master Quality Authenticated – sources. MQA is Meridian's revolutionary audio processing system that captures the essence of a

Product highlights

Reference preamplifier featuring Meridian enhancement technologies such as triple FIFO buffering, DSP upsampling and apodising filters to deliver the very best performance from any digital source.

Fully supports decoding of MQA sources for true studio quality replay – guaranteed.

ID41 card connects direct to a Meridian Sooloos Digital Media System to make the 818 an audio endpoint, rendering audio streamed from the Sooloos System. Magnetically-isolated design maximises audio quality.

Control the Digital Media System Play Queue with the remote control or front panel, or for complete control use the Core Control App for iPad.

Full range of analogue and digital inputs allowing the 818 to handle all your sources, with Meridian enhancements on the digital inputs.


High-resolution USB input for top quality audio from your computer system.

Meridian SpeakerLink connection for ultimate quality and convenience of installation when driving Meridian DSP Loudspeakers.

Support for DSD (DSD over PCM) with appropriate media player.

Meridian Audio Limited

meridian-audio.com



818v3 rear panel layout

studio master with advanced sampling technology and encapsulates it into a lossless stream or file. On replay, the sound of the original studio master is reproduced – guaranteed. On the 818, MQA sources are decoded and can then be rendered externally in the case of the digital outputs, and both decoded and rendered in the case of the analogue outputs.

The 818 supports the playback of DSD sources via DSD-over-PCM (DoP) from a suitable media player, using the USB or S/PDIF coax inputs.

818 connects directly to a Meridian Sooloos Digital Media System. When connected, the 818 becomes an audio endpoint and renders audio streamed from the Sooloos system. The card has been designed with particular attention paid to

magnetic isolation, which helps maximise the performance of the source without the need for external cable filtering.

Control commands sent through 818 can be used to manage music held in the Digital Media System current Play Queue, while the apps for iPad, iPhone and iPod Touch can all be used to control 818 as a source within a Meridian Sooloos system.

818 offers a diverse range of high-performance audio inputs, both analogue and digital. These allow all your audio sources to be switched and processed using the same powerful audio enhancing DSP as the internal Digital Media source. It also offers an elegant way to connect and control almost any audio source you might want to enjoy on a pair of Meridian DSP Loudspeakers.

A high-resolution USB input allows a simple high-quality connection to be made between your personal computer and the Reference Audio Core, allowing 818 to function as an external soundcard for your computer. This simple method of digital connection enhances the sound from all media on your computer, whether stored locally or streamed across a network or the internet, limited only by the source material.

818 Reference Audio Core features an advanced linear power supply design for minimum noise and maximum signal integrity.

818 is available in Black and the full range of Meridian Select colour options.

Outline Technical Specification

Stereo Outputs:

Analogue:

- 1x unbalanced on phono
- 1x balanced on XLR-3M
- Rendering of decoded MQA streams

Digital:

- Coaxial S/PDIF ≤96kHz/24-bit
- Twin SpeakerLink, RJ45 balanced (AES/EBU) digital interface for single-cable connection to other Meridian equipment, ≤96kHz/24-bit with MHR, and MQA signals for rendering by Meridian DSP loudspeakers

Stereo Inputs:

Analogue:

- 6x unbalanced on phono

Digital:

- 2x Coaxial S/PDIF ≤192kHz/24-bit, DoP
- 2x Toslink optical ≤96kHz/24-bit
- 1x SpeakerLink ≤192kHz/24-bit
- 1x Asynchronous USB ≤192kHz/24-bit, DoP
- MQA source decoding

Sources:

Meridian Sooloos System:

- RJ45 Ethernet connection

Comms:

Meridian Comms:

- 2x 240 degree 5-pin DIN
- 1x SpeakerLink input with Comms
- 2x SpeakerLink outputs with Comms

RS232:

- 9-pin D-sub, remote control & configuration

Triggers:

- 3x 12V (barrel connectors)

Construction:

- Black finish in metal and glass. Meridian Select colours also available.

Controls:

Front panel:

- Source, Play/Pause, Previous, Next, Mute, Volume+, Volume-, Off

Behind long door:

- Menu, Up, Down, Left, Right, F-Fwd, F-Rwd, Setup, Source, Display, Mute, Volume+, Volume-

Remote Control:

- Via MSR+ (supplied) and RS232

Display:

20-character LCD:

- With adjustable brightness and contrast.

Dimensions (HWD):

- 175 (6.9) x 480 (18.9)
- x 411 (16.2) mm (in)

Weight:

- 16.0 kg (35.2 lbs)

Power:

- Advanced linear power supply
- 110 - 120 Volt 50/60Hz
- 220 - 240 Volt 50/60Hz

Max Power Consumption:

- 40 Watts